

Please amend claims 1 and 19 as follows and cancel claims 2 and 20.

1. (Currently amended) A system comprising:

an interconnect;

a transmitting chip including a transmitter to produce a spread spectrum data signal to the interconnect in response to a spread spectrum clocking transmitting clock signal; and

a receiving chip coupled to the transmitting chip through the interconnect, the receiving chip including:

clock recovery circuitry to receive the spread spectrum data signal and a reference clock signal and in response thereto to produce an in phase clock signal which is in phase with the spread spectrum data signal and mirrors frequency changes in the spread spectrum data signal, wherein the spread spectrum data signal has embedded clock information and a varying frequency; and

a receiving gate to receive the spread spectrum data signal and the in phase clock signal and to gate the spread spectrum data signal to produce a gated data signal in response to the in phase clock signal; and

wherein the clock recovery circuitry includes mirroring circuitry to receive the spread spectrum data signal and the reference clock signal and in response thereto to produce a frequency mirrored clock signal that mirrors frequency changes in the spread spectrum data signal, a phase detector to receive the spread spectrum data signal and in response thereto to produce a phase information signal, and a phase interpolator to receive the phase information signal and the frequency mirrored clock signal and in response thereto to produce the in phase clock signal.

2. (Canceled)

3. (Previously presented) The system of claim 2, wherein the mirroring circuitry includes demodulator circuitry to create a signal representative of frequency changes in the spread spectrum data signal.

4. (Previously presented) The system of claim 3, wherein the mirroring circuitry includes an RF mixer to frequency modulate the reference clock signal and the signal representative of frequency changes in the spread spectrum data signal.

5. (Original) The system of claim 3, wherein the demodulator circuitry includes

histogram analysis.

6. (Previously presented) The system of claim 2, wherein the mirroring circuitry includes an RF mixer to frequency modulate the reference clock signal and a signal representative of frequency changes in the spread spectrum data signal.

7. (Original) The system of claim 1, further comprising a local reference source to produce the reference clock signal, wherein the reference clock signal has a constant frequency.

8. (canceled)

9. (Previously presented) The system of claim 1, further comprising a local reference source external to the receiving chip to produce the reference clock signal, wherein the reference clock signal has a constant frequency.

10. (Previously presented) The system of claim 1, wherein the system is included in a computer system.

11. (Previously presented) The system of claim 1, wherein the system is included in a communication system.

12. (Previously presented) A system comprising:

a receiving gate to receive a data signal and an in phase clock signal and to gate the data signal to produce a gated data signal in response to the in phase clock signal, wherein the data signal has embedded clock information and a varying frequency; and

clock recovery circuitry to receive the gated data signal and a reference clock signal and in response thereto to produce the in phase clock signal which is in phase with the data signal and mirrors frequency changes in the data signal, wherein the clock recovery circuitry includes:

a phase detector to receive the gated data signal and in response thereto to produce a phase information signal,

mirroring circuitry to receive the gated data signal and the reference clock signal and in response thereto to produce a frequency mirrored clock signal that mirrors frequency changes in the data signal, and

a phase interpolator to receive the phase information signal and the frequency mirrored clock signal and in response thereto to produce the in phase clock signal.

13. (Canceled)

14. (Previously presented) The system of claim 12, wherein the mirroring circuitry

includes demodulator circuitry to create a signal representative of frequency changes in the data signal.

15. (Original) The system of claim 14, wherein the mirroring circuitry includes an RF mixer to frequency modulate the reference clock signal and the signal representative of frequency changes in the data signal.

16. (Original) The system of claim 14, wherein the demodulator circuitry includes histogram analysis.

17. (Previously presented) The system of claim 12, wherein the mirroring circuitry includes an RF mixer to frequency modulate the reference clock signal and a signal representative of frequency changes in the data signal.

18. (Previously presented) The system of claim 12, further comprising:
a transmitting chip including a transmitter to produce the data signal to an interconnect in response to a spread spectrum clocking transmitting clock signal; and
a receiving chip coupled to the transmitting chip through the interconnect, the receiving chip including the clock recovery circuitry and the receiving gate.

19. (Currently amended) A system comprising:
clock recovery circuitry to receive a spread spectrum data signal and in response thereto to produce an in phase clock signal which is in phase with the spread spectrum data signal and mirrors frequency changes in the spread spectrum data signal, wherein the data signal has embedded clock information and a varying frequency; and

a receiving gate to receive the spread spectrum data signal and the in phase clock signal and to gate the spread spectrum data signal to produce a gated data signal in response to the in phase clock signal; and

wherein the clock recovery circuitry includes mirroring circuitry to receive the spread spectrum data signal and in response thereto to produce a frequency mirrored clock signal that mirrors frequency changes in the spread spectrum data signal, a phase detector to receive the spread spectrum data signal and in response thereto to produce a phase information signal, and a phase interpolator to receive the phase information signal and the frequency mirrored clock signal and in response thereto to produce the in phase clock signal.

20. (Canceled)

21. (Previously presented) The system of claim 20, wherein the mirroring circuitry includes demodulator circuitry to create a signal representative of frequency changes in the spread spectrum data signal.

22. (Previously presented) The system of claim 19, further comprising:
a transmitting chip including a transmitter to produce the spread spectrum data signal to an interconnect in response to a spread spectrum clocking transmitting clock signal; and
a receiving chip coupled to the transmitting chip through the interconnect, the receiving chip including the clock recovery circuitry and the receiving gate.

23. (Previously presented) A system comprising:
a receiving gate to receive a data signal and an in phase clock signal and to gate the data signal to produce a gated data signal in response to the in phase clock signal, wherein the data signal has embedded clock information and a varying frequency; and
clock recovery circuitry to receive the gated data signal and in response thereto to produce the in phase clock signal which is in phase with the data signal and mirrors frequency changes in the data signal, wherein the clock recovery circuitry includes:
a phase detector to receive the data signal and in response thereto to produce a phase information signal,
mirroring circuitry to receive the data signal and in response thereto to produce a frequency mirrored clock signal that mirrors frequency changes in the data signal, and
a phase interpolator to receive the phase information signal and the frequency mirrored clock signal and in response thereto to produce the in phase clock signal.

24 (Canceled)

25. (Previously presented) The system of claim 23, wherein the mirroring circuitry includes demodulator circuitry to create a signal representative of frequency changes in the data signal.

26. (Previously presented) The system of claim 23, further comprising:
a transmitting chip including a transmitter to produce the data signal to an interconnect in response to a spread spectrum clocking transmitting clock signal; and
a receiving chip coupled to the transmitting chip through the interconnect, the receiving chip including the clock recovery circuitry and the receiving gate.